

CYANSKY™



M2
User Manual

CYANSKY M2 is a rechargeable and compact EDC flashlight with 200 lumens output and 24 hours runtime. With 3 output modes, it is good for use in various situations. Besides, featuring Ip68 waterproof rating and 2 meter impact resistance, M2 is capable of all weather use. The length is 34mm, just as long as the length of a CR123A battery. It's the best choice for your everyday lighting.


Product features:

- * Cree XP-E2 R3LED with a lifespan of 50,000 hours.
- * Powered by one rechargeable 200mAh Li-ion battery pack.
- * Intelligent digitally regulated output maintains constant brightness.
- * M2 has voltage display function.
- * Easy one-switch operation.
- * Micro USB rechargeable
- * Made of durable high-strength aluminum.
- * Premium type HAIII hard-anodized anti-abrasive finish.
- * Reflector is made of vacuum plating aluminum.
- * Toughened ultra-clear glass lens with anti-reflective coating.
- * Low-voltage warning
- * Max 200 lumens
- * Max 24 hours runtime
- * Ip68 waterproof
- * 18.5 grams
- * Size: 34mm×20mm (Length×Diameter)

Technical Parameters

M2	Low	Med	High	Strobe
OUTPUT (Lumens)	5	20	200	200
RUNTIME (Hours)	24	5	0.8	1.6
DISTANCE (Meters)	13	26	83	83
INTENSITY (Candelas)	43	169	1720	1720

Notice: The above mentioned parameters (lab-tested by using a 200mAh Li-ion battery pack) may vary between flashlights, batteries and environments.



CYANSKY Ltd.co

Website: www.freasygears.com
Email: freasy@freasygears.com
Tel: 0086-752-557 7002
Address: Room 505#, Jinhai Building B, Guantai Road 56#, Nancheng, Dongguan, China



Operating Instruction:

On/Off: Press and hold the switch for 0.5 seconds to turn on/off the light.

Output Selection: With the lamp switched on, single click the switch to cycle through Low—Med—High.

Instant Strobe: Press and hold the switch for 1.0 second to enter instant Strobe no matter the switch on or off.

Intelligent Protection:

The light will accumulate a lot of heat when it is working at High mode. When the light is working for 1 minute, the flashlight will automatically step down to 100 lumens to avoid overheating.

Low-voltage Warning:

When the voltage is lower than 3.0V, the battery level indicator on the switch will flash in red for 3 times every 5 minutes to remind battery replacement or charging

Low-voltage downshift:

When the voltage is lower than 3.0V the flashlight will step down automatically to a lower brightness level until Eco output is reached. The flashlight will not turn off until the battery level runs out.

Battery Level Indication:

- * Single click the switch when the lamp is switched off, the battery level indicator will display the battery status for 3 seconds. And you can turn on the lamp when the battery level indicator is on.
- * Green constant on: voltage is more than 85%
- * Green flasher: voltage is more than 50% and less than 85%
- * Red constant on: voltage is more than 25% and less than 50%
- * Red flasher: voltage is less than 25%

Attentions:

- * If the light will not be used for an extended period, remove the battery from the light, or the light could be damaged by electrolyte leakage or battery explosion.
- * Children use this product must under the guidance of adults.
- * This flashlight is a high-intensity lighting device capable of causing eye damage to the user. Avoid shining the flashlight directly into eyes.
- * Do not put the light with battery in it into the fire, otherwise it will explode.
- * Do not put the light with the battery cover opened into the water.
- * Do not put the positive and negative of battery reversely.

Warranty

- 15 days free replacement: CYANSKY will offer a new replacement within 15 days of purchase for any manufacturing defects if the problem occurs in normal use. In case the model has been discontinued, the customer will receive a similar or improved model in time.
- 60 Months free repairs: CYANSKY will offer free repair within 60 months (5 years) for lights from the date of purchase if problem happens with normal use.
- Limited lifetime warranty: For lights past the free repair warranty period, we provide lifetime repairs but will charge for parts. The distributor or dealer will notify customers of the cost in advance.

CYANSKY warranty service does not cover any damages or failure caused by:

- Excessive dropping, unauthorized modification or reconstruction.
- Improper use, storage or maintenance (such as reverse putting of battery).
- Battery leakage.
- Salt water and corrosive damage to the unit.
- Damage caused by improper maintenance.
- Ordinary wear and tear/color fading.

Included:

M2 flashlight, USB cable, Lanyard, User manual, Warranty card, Built-in 200mAh rechargeable battery pack.

双面印刷 折后尺寸：50x47mm